



#### ADC.3.E...

"A09" DC Coils	Ch. I PAGE 7
STANDARD CONNECTORS	CH. I PAGE 19

# ADC.3... DIRECTIONAL CONTROL VALVES CETOP 3 SOLENOID OPERATED WITH REDUCED OVERALL SIZE OFFICE

The ARON NG6 directional control valves are designed for subplate mounting with an interface in accordance with UNI ISO 4401 - 03 - 02 - 0 - 94 standard (ex CETOP R 35 H 4.2-4-03).

The use of solenoids with wet armatures allows an extremely safe construction completely dispensing with the need for dynamic seal. The solenoid tube is screwed directly onto the valve casting whilst the coil is kept in position by a ring nut.

The operation of the directional valve is electrical. The centring is achieved by means of calibrated length springs which, once the impulse is over, immediately reposition the spool in the neutral position. To improve the valve performance, different springs are used for each spool.

The solenoids, constructed with a protection class of IP65 in accordance with BS 5490 standards, are available in direct current form and different voltage. The electrical controls are equipped with an emergency manual control inserted in the tube.


The ADC.3 valve uses shorter solenoids than the standard AD.3.E to reduce the overall dimensions

The solenoid coils are normally arranged for DIN 43650 ISO 4400 type connectors (standard version). On request, could be available the following coil connection variants: AMP Junior connections; flying leads connections, with or without integrated diode; Deutsch connections with bidirectional integrated diode.

The recommended fluids are hydraulic mineral based oils in accordance with DIN 51524 and it is recommended that filters should be fitted to ensure a maximum contamination level of class 10 in accordance with NAS 1638,  $\beta_{sc}$  $\geq$ 75.

- 250 bar
30 l/min
3 Hz
100% ED
10 ÷ 500 mm²/s
-25°C ÷ 75°C
-25°C ÷ 60°C
class 10 in accordance
S 1638 with filter B <sub>25</sub> ≥75
d 1,25 Kg
ds 1,5 Kg

#### PRESSURE DROPS



Spool	Connections				
type	P→A	Р→В	A→T	В→Т	P→T
01	4	4	4	4	
02	6	6	6	6	6
03	4	4	6	6	
04	3	3	2	2	5
15E-16E	6	3	1	5	
15F-16F	3	6	5	1	
	Curve No.				

The diagram at the side shows the pressure drop curves for spools during normal usage. The fluid used is a mineral oil with a viscosity of  $46 \text{ mm}^2/\text{s}$  at  $40 \text{ C}^\circ$ ; the tests have been carried out at a fluid temperature of  $40 \text{ C}^\circ$ . For higher flow rates than those in the diagram, the losses will be those expressed by the following formula:

$$\Delta p1 = \Delta p \ x \ (Q1/Q)^2$$

where  $\Delta p$  will be the value for the losses for a specific flow rate Q which can be obtained from the diagram,  $\Delta p1$  will be the value of the losses for the flow rate Q1 that is used.



1

#### **O**RDERING CODE

Onderning Code		
ADC	Directional valve	
3	CETOP 3/NG6	
E	Electrical operator	
**	Spool (tables at the side)	
*	Mounting (table 1)	
*	Voltage (table 2)	
**	Variants (table 3)	
1	Serial No.	

	Tab.1 - Mountine	G
	Standard	
С	A O B W	
Е	a/AOM	
F	MOB VP	
Spi	ECIALS (WITH PRICE INCREASING)	
G	WAO TO	
Н	a/OBW	

STANDARD SPOOL * Spools with price increasing			
Two	SOLENOIDS, SPR	ING CENTRE	"C" MOUNTING
Spool type	MA OB Wb	Covering	Transient position
01		+	
02	<u> </u>	-	XHHHD
03		+	
04*		-	

ONE SOLENOID, SIDE A "E" MOUNTING			
Spool type	a/AOW	Covering	Transient position
01		+	XIIII
02	a/ X   W	-	
03		+	
04*		-	
15	a/ \\	-	
16	B/ X   W	+	X1.1[]

0	ONE SOLENOID, SIDE B "F" MOUNTING			
Spool type	M O B /P	Covering	Transient position	
01	WHITE	+		
02	w	-		
03	W###	+		
04*	WHIXE	-	HHX	
15	wXIII-	-	XHII	
16	wXIII-	+		

#### TAB.2 - A09 (27 W) COIL

	DC VOLTAGE		
M N P	12V 24V 48V* 110V*	115Vac/50Hz 120Vac/60Hz with rectifier	
Z X W	102V* ∢ 205V* ∢ With	240Vac/60Hz	
Voltage codes are not stamped on the plate, their are readable on the coils.			
* Spec	cial voltage	е	


#### Tab.3 - Variants (\*\*)

No variant (without connectors)	S1
Viton	SV
Emergency button	ES
Rotary emergency button	P2 (*)
Rotary emergency button (180°)	R5 (*)
Variant with lever for emergency button	LF
AMP Junior connection	AJ
Coil with flying leads (250 mm)	FL
Coil with flying leads (130 mm) with diode	LD
Deutsch connection with bidirectional dio	de CX
Other variants relate to a special design	

### (\*) P2 and R5 Emergency tightening torque max. $6 \div 9 \text{ Nm} / 0.6 \div 0.9 \text{ Kgm}$ with CH n. 22

- (\*\*) All variants are considered without connectors. The connectors must be order separately. See Ch. I Page 19
- The AMP Junior coil and with the flying leads (with or without diode) coils are available in 12V or 24V DC voltage only.
- •The Deutsch coil with bidirectional diode is available in 12V DC voltage only.

#### LIMITS OF USE (MOUNTING C-E-F)



Spool type	n° curve
01 02 03 04 15-16	2 1 3 3 1(4*)

 $(4^*)$  = 15 and 16 spools used as 2 or 3 way, follow the curve  $n^{\circ}4$ 

The tests have been carried out with solenoids operating temperature and a voltage 10% less than rated voltage with a fluid temperature of 50 C°. The fluid used was a mineral oil with a viscosity of 46 mm²/s at 40 degrees C. The values in the diagram refer to tests carried out with the oil flow in two directions simultaneously (e.g., from P to A and at the same time B to T).

In the cases where valves 4/2 and 4/3 are used with the flow in one direction only, the limits of use could have variations which may even be negative (See curve No 4 and Spool No 15-16). The tests were carried out with a counter-pressure of 2 bar at T port.

## **O**VERALL DIMENSIONS ø9 ø5.5 92.5 OR 2-012/90 129.3 178.1 E = Manual override 19 Support plane specifications **0**.03 Fixing screws UNI 5931 M5x30 10.4 with material specifications min. 8.8 Tightening torque 5 ÷ 6 Nm / 0.5 ÷ 0.6 Kgm



### A09 DC coils



Type of protection	
(in relation to connector used)	IP 65
Number of cycle	18.000/h
Supply tolerance	±10%
Ambient temperature	-30°C ÷ 60°C
Duty cycle	100% ED
Insulation class wire	Н
Weight	0,215 Kg

- The AMP Junior coil and with the flying leads (with or without diode) coils are available in 12V or 24V DC voltage only.
- The Deutsch coil with bidirectional diode is available in 12V DC voltage only.

VOLTAGE (V)         MAX WINDING TO (AMBIENT TEMPE)           12V         123           24V         123           48V*         123           102V*         123           110V*         123           205V*         123	RATURE 25°C) PC PC PC PC PC	RATED POWER (W)  27 27 27 27 27 27 27 27 27	RESISTANCE AT 20°C (OHM) ±7%  5.3 21.3 85.3 392 448 1577  ETA09 - 04/2001/e	AMP JUNIOR (AJ)	DEUTSCH COIL + BIDIR. DIODE (CX) DT04 - 2P
ES MANUAL EMERGENCY	1 ' '	ROTARY GENCYE	EMERGE	ROTARY NCY 180°	FLYING LEADS (FL) LEADS + DIODE (LD)

(\*) P2 and R5 Emergency tightening torque max.  $6 \div 9 \text{ Nm} / 0.6 \div 0.9 \text{ Kgm}$  with CH n. 22